


Conformal Mapping (H.1)

20160630

Copyright (c) 2015 - 2016 Young W. Lim.

Permission is granted to copy, distribute and/or modify this document under the terms of the GNU Free Documentation License, Version 1.2 or any later version published by the Free Software Foundation; with no Invariant Sections, no Front-Cover Texts, and no Back-Cover Texts. A copy of the license is included in the section entitled "GNU Free Documentation License".

Mapping $w = f(z)$



$$w = f(z) \\ = u + i v$$

$$w = f(x + iy) \\ = u(x, y) + i v(x, y)$$

$$\boxed{z = x + iy} \longrightarrow \boxed{w = u + iv}$$

image of z
under f

Images of Curves

$$z = x + iy$$

$$w = u + iv$$



image of z
under f

$$z(t) = x(t) + iy(t)$$

$$w(t) = u(t) + iv(t)$$

$$w = f(z(t))$$

$$= u(x(t), y(t)) + iv(x(t), y(t))$$



$$f(z) = z + z_0 \quad \text{translation}$$

$$g(z) = e^{i\theta} \cdot z \quad \text{rotation}$$

$$h(z) = \alpha z \quad \text{magnification}$$

α : fixed positive real number

Real Power Function

$$f(z) = z^\alpha \quad \alpha: \text{a fixed positive real number}$$

$$z : \quad 0 \leq \operatorname{Arg}(z) \leq \theta_0$$

$$w = f(z) : \quad 0 \leq \operatorname{Arg}(w) \leq \alpha \theta_0$$

Angle Preserving Mappings

A complex mapping $w = f(z)$
defined on domain D

Conformal at $z = z_0$ in D

when f preserves the angle
between any 2 curves in D
that intersects at z_0

C_1 and C_2 intersect in D at z_0
the corresponding images C'_1 and C'_2

the angle between C_1 and C_2
the angle between C'_1 and C'_2

$$|z'_1 - z'_2|^2 = |z'_1|^2 + |z'_2|^2 - 2|z'_1||z'_2| \cos \theta$$

$$\theta = \cos^{-1} \left(\frac{|z'_1|^2 + |z'_2|^2 - |z'_1 - z'_2|^2}{2|z'_1||z'_2|} \right)$$

$$\varphi = \cos^{-1} \left(\frac{|w'_1|^2 + |w'_2|^2 - |w'_1 - w'_2|^2}{2|w'_1||w'_2|} \right)$$

$f(z)$: analytic in the domain D

$f'(z_0) \neq 0 \rightarrow f$ is conformal at $z = z_0$

$$z = z(t)$$

$$w = f(z(t))$$

$$w' = f'(z(t)) z'(t)$$

C_1 and C_2 intersect in D at z_0

$$w'_1 = f'(z_0) z'_1$$

$$w'_2 = f'(z_0) z'_2$$

$$\varphi = \cos^{-1} \left(\frac{|w'_1|^2 + |w'_2|^2 - |w'_1 - w'_2|^2}{2 |w'_1| |w'_2|} \right)$$

$$= \cos^{-1} \left(\frac{|f'(z_0) z'_1|^2 + |f'(z_0) z'_2|^2 - |f'(z_0) z'_1 - f'(z_0) z'_2|^2}{2 |f'(z_0) z'_1| |f'(z_0) z'_2|} \right)$$

$$= \cos^{-1} \left(\frac{|z'_1|^2 + |z'_2|^2 - |z'_1 - z'_2|^2}{2 |z'_1| |z'_2|} \right)$$

$$= 0$$

Transform Theorem for Harmonic Functions

f : analytic function $D \rightarrow D'$

u : harmonic in D'

the real-valued function $u(x, y) = u(f(z))$
harmonic in D

Linear Fractional Transformations

$$T(z) = \frac{az + b}{cz + d}$$


$$T'(z) = \frac{ad - bc}{(cz + d)^2}$$

$$\lim_{z \rightarrow z_0} T(z) = \infty \quad z_0 = -\frac{d}{c}$$

$$\lim_{|z| \rightarrow \infty} T(z) = \lim_{|z| \rightarrow \infty} \frac{a + b/z}{c + d/z} = \frac{a}{c}$$


Circle Preserving Property

$$T(z) = \frac{az + b}{cz + d} \quad \text{Linear Fractional Trans.}$$

 $c \leftarrow 0$


$$T(z) = A z + B \quad \text{Linear Trans}$$

Linear Complex Mapping

Composite of 
rotation
magnification
translation

circle in the z -plane \longrightarrow circle in the w -plane

$$T(z) = \frac{az+b}{cz+d} \quad \text{Linear Fractional Trans.}$$

 $c \neq 0$

$$\begin{aligned} T(z) &= \frac{bd-ad}{c} \frac{1}{cz+d} + \frac{a}{c} \\ &= A \frac{1}{cz+d} + B \quad z_1 = cz+d \\ &= A \frac{1}{z_1} + B \quad z_2 = \frac{1}{z_1} \\ &= A z_2 + B \end{aligned}$$

General Linear Fractional Trans.

composite of two linear functions
the inversion $w = 1/z$

$$|z - z_1| = r \quad w = \frac{1}{z}$$

$$\left| \frac{1}{w} - \frac{1}{w_1} \right| = \frac{|w - w_1|}{|w||w_1|} = r$$

$$|w - w_1| = r |w_1| |w - 0|$$

$$|w - w_1| = \lambda |w - w_2|$$

$\lambda = 1$ line

$\lambda \neq 1, \lambda > 0$ circle


the image of the circle $|z - z_1| = r$

under the inversion $w = 1/z$

a circle except when $r = 1/|w_1| = |z_1|$

Circle - Preserving Property

A Linear Fractional Transformation





To solve Dirichlet problems
construct special functions
that map a given circular region R
to a target region R'
where the corresponding Dirichlet problem
is solvable.

A Circular Boundary - by 3 points

Find a linear frac trans $w = T(z)$

z_1, z_2, z_3 in $R \rightarrow w_1, w_2, w_3$ in R'

interior of $R \rightarrow$ interior of R'



$$T(z) = \frac{az + b}{cz + d} \quad A = \begin{pmatrix} a & b \\ c & d \end{pmatrix}$$

$$T_1(z) = \frac{a_1 z + b_1}{c_1 z + d_1} \quad A_1 = \begin{pmatrix} a_1 & b_1 \\ c_1 & d_1 \end{pmatrix}$$

$$T_2(z) = \frac{a_2 z + b_2}{c_2 z + d_2} \quad A_2 = \begin{pmatrix} a_2 & b_2 \\ c_2 & d_2 \end{pmatrix}$$

$$w = T(z) = T_2(T_1(z)) \quad A = A_2 A_1$$

$$z = T^{-1}(w) \quad \text{adj}(A)$$

Triples of Triples

$$T(z) = \frac{z - z_1}{z - z_3} \frac{z_2 - z_3}{z_2 - z_1}$$

$$\begin{cases} T(z_1) = 0 \\ T(z_2) = 1 \\ T(z_3) = \infty \end{cases}$$

CROSS ratio of the complex numbers z, z_1, z_2, z_3

$$S(w) = \frac{w - w_1}{w - w_3} \frac{w_2 - w_3}{w_2 - w_1}$$

$$\begin{cases} S(w_1) = 0 \\ S(w_2) = 1 \\ S(w_3) = \infty \end{cases}$$

$$\begin{cases} S^{-1}(0) = w_1 \\ S^{-1}(1) = w_2 \\ S^{-1}(\infty) = w_3 \end{cases}$$

$$\begin{cases} T(z_1) = 0 \\ T(z_2) = 1 \\ T(z_3) = \infty \end{cases}$$

$$\begin{cases} S^{-1}(0) = w_1 \\ S^{-1}(1) = w_2 \\ S^{-1}(\infty) = w_3 \end{cases}$$

$w = S^{-1}(T(z))$ maps the triple z_1, z_2 , and z_3
to the triple w_1, w_2 , and w_3



$$S(w) = T(z)$$

$$\frac{w - w_1}{w - w_3} \frac{w_2 - w_3}{w_2 - w_1} = \frac{z - z_1}{z - z_3} \frac{z_2 - z_3}{z_2 - z_1}$$

Riemann Mapping Theorem

D' a simply connected domain
with at least one boundary point

the existence of an analytic function g
which conformally maps
the unit open disk $|z| < 1$
onto D'



Schwarz - Christoffel Transformation

Unlike the Riemann mapping theorem


can specify

a form of for the derivative $f'(z)$

of a conformal mapping $f(z)$


from the upper half plane

to a bounded or unbounded polygonal region




Lin. Frac. Trans

conformal map f




Bounded



Lin. Frac. Trans

conformal map f



Unbounded

mapping



$$f(z) = [z - x_1]^{\alpha/\pi}, \quad 0 \leq \alpha < 2\pi$$

on the upper half plane $y \geq 0$


$$\zeta = [z - x_1]$$

$$w = \zeta^{\alpha/\pi}$$


$$\begin{matrix} [0, \pi] \\ \downarrow \\ [0, \alpha] \end{matrix}$$



$$\begin{aligned} f'(z) &= \frac{\alpha}{\pi} (z - x_1)^{\alpha/\pi - 1} \\ &= A (z - x_1)^{\alpha/\pi - 1} \end{aligned}$$



$$f(z) = [z - z_1]^{\alpha/\pi} \quad 0 \leq \alpha < 2\pi$$



Arg $[0, \pi]$
 \downarrow \downarrow
 $[0, \alpha]$

$$f(z) = [z - z_1]^{\alpha/\pi} \quad 0 \leq \alpha < 2\pi$$

$$\begin{aligned} f'(z) &= \frac{\alpha}{\pi} [z - z_1]^{\alpha/\pi - 1} \\ &= A [z - z_1]^{\alpha/\pi - 1} \end{aligned}$$

Assume $f(z)$ analytic in the upper half plane ($y \geq 0$)

$$f'(z) = A (z - x_1)^{\frac{\alpha_1}{\pi} - 1} (z - x_2)^{\frac{\alpha_2}{\pi} - 1}$$


$$x_1 < x_2$$

$$\arg(w'(t)) = \text{const} \Rightarrow$$

a curve $w = w(t)$: a line
in the w -plane


$$f'(t) = A (t - x_1)^{\frac{\alpha_1}{\pi} - 1} (t - x_2)^{\frac{\alpha_2}{\pi} - 1}$$

$$\begin{aligned}\arg\{f'(t)\} &= \operatorname{Arg}(A) \\ &+ \left(\frac{\alpha_1}{\pi} - 1\right) \operatorname{Arg}(t - x_1) \\ &+ \left(\frac{\alpha_2}{\pi} - 1\right) \operatorname{Arg}(t - x_2)\end{aligned}$$



$$\begin{cases} t < x_1 & \operatorname{Arg}(t - x_1) = \pi \\ t > x_1 & \operatorname{Arg}(t - x_1) = 0 \end{cases}$$

$$\begin{cases} t < x_2 & \operatorname{Arg}(t - x_2) = \pi \\ t > x_2 & \operatorname{Arg}(t - x_2) = 0 \end{cases}$$



$\arg\{f'(t)\}$

$$\begin{aligned} &\text{Arg}(A) \\ &+ (\alpha_1 - \pi) \\ &+ (\alpha_2 - \pi) \end{aligned}$$

const

$$+ (\pi - \alpha_1)$$


$$\begin{aligned} &\text{Arg}(A) \\ &+ 0 \\ &+ (\alpha_2 - \pi) \end{aligned}$$

const

$$+ (\pi - \alpha_2)$$

$$\begin{aligned} &\text{Arg}(A) \\ &+ 0 \\ &+ 0 \end{aligned}$$

const




$$\operatorname{Arg}(A) + (\alpha_1 - \pi) + (\alpha_2 - \pi)$$

$$\operatorname{Arg}(A) + (\alpha_2 - \pi)$$


$$\operatorname{Arg}(A)$$

$$\arg\{f'(t)\} = \begin{cases} \operatorname{Arg}(A) + (\alpha_1 - \pi) + (\alpha_2 - \pi) & [t < x_1] \\ \operatorname{Arg}(A) + (\alpha_2 - \pi) & [x_1 < t < x_2] \\ \operatorname{Arg}(A) & [t > x_2] \end{cases}$$



$$w = f(t) \quad x_1 < t < x_2$$

$$w = f(t) \quad t > x_2$$



Schwarz - Christoffel Formula

$f(z)$ analytic in the upper half-plane $y > 0$

$$f'(z) = A(z - x_1)^{\alpha_1/\pi - 1} (z - x_2)^{\alpha_2/\pi - 1} \cdots (z - x_n)^{\alpha_n/\pi - 1}$$

$$x_1 < x_2 < \cdots < x_n$$

$$0 < \alpha_i < 2\pi \quad i=1, \dots, n$$

$f(z)$ maps the upper half-plane $y > 0$

to a polygonal region

with interior angles $\alpha_1, \alpha_2, \dots, \alpha_n$

① can select the location of 3 points
 x_k on the x -axis

careful selection simplifies the computation of $f(z)$

other remaining points depends on the shape of
 the target polygon

② A general formula for $f(z)$

$$f'(z) = A(z - x_1)^{\alpha_1/\pi-1} (z - x_2)^{\alpha_2/\pi-1} \cdots (z - x_n)^{\alpha_n/\pi-1}$$

$$f(z) = A \left[(z - x_1)^{\alpha_1/\pi-1} (z - x_2)^{\alpha_2/\pi-1} \cdots (z - x_n)^{\alpha_n/\pi-1} \right] dz + B$$

$$= A g(z) + B$$

$$g(z) = \left[(z - x_1)^{\alpha_1/\pi-1} (z - x_2)^{\alpha_2/\pi-1} \cdots (z - x_n)^{\alpha_n/\pi-1} \right] dz$$

$$h(z) = Az + B$$

$\begin{cases} \text{magnify} \\ \text{rotate} \\ \text{translate} \end{cases}$


the image polygon produced by $g(z)$

③


If the polygon regions are bounded

only $n-1$ of the n interior angles

Should be included in the Schwartz-Christoffel formula



Bounded



Bounded

$\alpha_1, \alpha_2, \alpha_3, \alpha_4$
are sufficient to
determine Schwartz-
Christoffel formula

Laplace Equations

$$\frac{\partial^2 u}{\partial x^2} + \frac{\partial^2 u}{\partial y^2} = 0 \quad 0 < x < a \quad 0 < y < b$$

Neuman
Condition

$$(BC) \quad \left. \frac{\partial u}{\partial x} \right|_{x=0} = 0, \quad \left. \frac{\partial u}{\partial x} \right|_{x=a} = 0 \quad 0 < y < b$$

Dirichlet
Condition

$$(BC) \quad u(x, 0) = 0, \quad u(x, b) = f(x) \quad 0 < x < a$$

Dirichlet
Condition

$$(BC) \quad u(0, y) = 0, \quad u(a, y) = 0 \quad 0 < y < b$$

Dirichlet
Condition

$$(BC) \quad u(x, 0) = 0, \quad u(x, b) = f(x) \quad 0 < x < a$$

$$u(x, b) = f(x)$$

$$u(0, y) = 0$$

$$u(a, y) = 0$$

$$u(x, 0) = 0$$

Dirichlet Problem: Superposition

$$\frac{\partial^2 u}{\partial x^2} + \frac{\partial^2 u}{\partial y^2} = 0 \quad 0 < x < a, \quad 0 < y < b$$

$$u(0, y) = F(y)$$

$$u(x, 0) = f(x)$$

$$u(a, y) = G(y)$$

$$u(x, b) = g(x)$$

$$0 < y < b$$

$$0 < x < a$$

$$\frac{\partial^2 u_1}{\partial x^2} + \frac{\partial^2 u_1}{\partial y^2} = 0 \quad 0 < x < a, \quad 0 < y < b$$

$$u_1(0, y) = 0$$

$$u_1(x, 0) = f(x)$$

$$u_1(a, y) = 0$$

$$u_1(x, b) = g(x)$$

$$0 < y < b$$

$$0 < x < a$$

$$\frac{\partial^2 u_2}{\partial x^2} + \frac{\partial^2 u_2}{\partial y^2} = 0 \quad 0 < x < a, \quad 0 < y < b$$

$$u_2(0, y) = F(y)$$

$$u_2(x, 0) = 0$$

$$u_2(a, y) = G(y)$$

$$u_2(x, b) = 0$$

$$0 < y < b$$

$$0 < x < a$$

Harmonic Functions

$$\frac{\partial^2 u}{\partial x^2} + \frac{\partial^2 u}{\partial y^2} = 0 \quad \frac{\partial^2 v}{\partial x^2} + \frac{\partial^2 v}{\partial y^2} = 0$$

the u & v parts of an analytic function
cannot be chosen arbitrarily


both u and v must satisfy Laplace eq

the real-valued function $\phi(x, y)$

- has continuous

2nd order partial derivatives
in a domain D

- satisfies Laplace eq



$\phi(x, y)$: harmonic in D

$$f(z) = u(x, y) + i v(x, y)$$

analytic in domain D



the function $u(x, y)$ & $v(x, y)$ are harmonic functions

Harmonic Conjugate Functions

⑥ $f(z) = u(x, y) + i v(x, y)$ analytic in D
 $\Rightarrow u, v$: harmonic in D

given $u(x, y)$: harmonic in D
find $v(x, y)$: harmonic in D
such that $u(x, y) + i v(x, y)$: analytic in D


u, v : harmonic conjugate function

Harmonic Functions & the Dirichlet Problem

Transformation Theorem for Harmonic Functions


f : analytic function

that maps a domain D onto a domain D'



real valued function $u(x, y) = \text{U}(f(z))$

u is harmonic in D \leftarrow U is harmonic in D'



① find conformal mapping $w = f(z)$

the original region (R) \longrightarrow the image region (R')

↓
many explicit solutions
to the Dirichlet
problems are known

② Transfer the boundary conditions

the boundary of (R) \longrightarrow the boundary of (R')

the value of u
at a boundary
point ξ

the value of U
at a boundary
point $f(\xi)$

③ Solve the corresponding Dirichlet problem in R'

④ the solution to the original Dirichlet problem

$$u(x, y) = U(f(z))$$

Poisson Integral Formulas

Dirichlet problems

in the upper half plane $y \geq 0$


in the unit disk $|z| \leq 1$

The Poisson integral formula
for the upper half plane

a solution by expressing
the value of a harmonic function $u(x, y)$
at a point in the interior of
the upper half plane
in terms of on the boundary $y = 0$


Formulas for the upper half plane

Boundary conditions on $y=0$



$$u(x, y) = \frac{u_i}{\pi} [\text{Arg}(z-b) - \text{Arg}(z-a)]$$

$$u(x, y) = \frac{u_i}{\pi} \text{Arg} \left(\frac{z-b}{z-a} \right)$$



$$u(x, 0) = u_i \quad x_{i-1} \leq x \leq x_i$$

$$u(x, 0) = 0 \quad x < x_{i-1}, \quad x_i < x$$

$$u(x, y) = \sum_{i=1}^n \frac{u_i}{\pi} [\operatorname{Arg}(z - x_i) - \operatorname{Arg}(z - x_{i-1})]$$

$$= \frac{1}{\pi} \sum_{i=1}^n u_i \theta_i(z)$$

$$\operatorname{Arg}(z - t) = \tan^{-1} \left(\frac{y}{x-t} \right) \quad [0, \pi]$$

$$\frac{d}{dt} \operatorname{Arg}(z - t) = \frac{y}{(x-t)^2 + y^2}$$

$$\begin{aligned}
 u(x, y) &= \frac{1}{\pi} \sum_{i=1}^n u_i \left[\operatorname{Arg}(z - x_i) - \operatorname{Arg}(z - x_{i+1}) \right] \\
 &= \frac{1}{\pi} \sum_{i=1}^n \int_{x_{i+1}}^{x_i} u_i \left[\frac{d}{dt} \operatorname{Arg}(z - t) \right] dt \\
 &= \frac{1}{\pi} \sum_{i=1}^n \int_{x_{i+1}}^{x_i} u_i \left[\frac{y}{(x-t)^2 + y^2} \right] dt
 \end{aligned}$$

$$u(x, y) = \frac{y}{\pi} \int_{-\infty}^{+\infty} \left[\frac{u(t, 0)}{(x-t)^2 + y^2} \right] dt$$

Poisson Integral Formula for the UHP

$u(x, 0)$ piecewise continuous function
on every finite interval
bounded on $-\infty < x < +\infty$

$$u(x, y) = \frac{y}{\pi} \int_{-\infty}^{+\infty} \frac{u(t, 0)}{(x-t)^2 + y^2} dt$$

\Rightarrow the solution of the corresponding Dirichlet problem
on the upper half-plane $y \geq 0$

Formula for the Unit Disc

$u(e^{i\theta})$ bounded and piecewise continuous
for $-\pi \leq \theta \leq +\pi$

Then the solution to the corresponding Dirichlet problem
on the open unit disk $|z| < 1$

$$u(x, y) = \frac{1}{2\pi} \int_{-\pi}^{\pi} u(e^{it}) \frac{1 - |z|^2}{|e^{it} - z|^2} dt$$

Geometric Interpretation

$$a \left(\frac{\partial^2 u}{\partial x^2} + \frac{\partial^2 u}{\partial y^2} \right) = \frac{\partial^2 u}{\partial t^2}$$

Fourier Series Form

$$U_n(r, \theta) = r^n \cos n\theta$$

$$V_n(r, \theta) = r^n \sin n\theta$$

a_0, a_n, b_n : the Fourier coefficients of $U(e^{i\theta})$
 $-\pi \leq \theta \leq +\pi$

Superposition principle

$$U(r, \theta) = \frac{a_0}{2} + \sum_{n=1}^{\infty} (a_n r^n \cos n\theta + b_n r^n \sin n\theta) \quad \text{harmonic}$$

$$U(1, \theta) = \frac{a_0}{2} + \sum_{n=1}^{\infty} (a_n \cos n\theta + b_n \sin n\theta) = U(e^{i\theta})$$

the solution of the Dirichlet problem

$$U(r, \theta) = \frac{1}{2\pi} \int_{-\pi}^{\pi} U(e^{i\theta}) \frac{1 - |z|^2}{|e^{it} - z|^2} dt$$

$$= \frac{a_0}{2} + \sum_{n=1}^{\infty} (a_n r^n \cos n\theta + b_n r^n \sin n\theta)$$